

- **Item Number**
CH20S
- **Name**
20 Cue Wireless Firing System [Standard]
- **Description**
20 Cue Wireless Firing System with variable delay Sequencer, various firing modes and the ability to be connected to other 20 Cue Wireless Firing Systems.
- **Size**
24 x 15 x 8 cm.
- **Weight**
1.3 Kg.
- **Construction Material**
Black plastic.
- **Antenna**
23 cm telescopic.
- **Firing Technology**
No relays and no moving parts. MOSFET transistors are used to fire the cues. The system is completely safe when bumped or vibrated.
- **Power**
 - Internal 12 volt 1.3 Ah Sealed Lead Acid battery.
 - External 15 volt DC charging connector.
 - UK 3 Pin 110 – 240 volt charger supplied.
- **Security**
 - 2 x metal arming keys.
 - Digital encoding technology secures the radio link.
- **Sequencer**
0.01 – 9.99 second variable delay sequencer.
- **Igniter Test**
Visual continuity test for each cue.
- **Firing Modes**
Each mode can be disabled by the user for safety.
 - **Direct Fire**
Simple direct firing of each cue.
 - **Step Fire**
Fire each cue on each successive button press.
 - **Continuous Fire**
Fire all cues in sequence with a 0.01 to 9.99 second delay between cues.
 - **All Fire**
Fire all cues with 1 button press.
- **Expansion**
 - **Up to 60 Cues**
Program up to 3 receivers with 1 transmitter and have all firing modes available to all 60 cues from across 3 receivers.
 - **Up to 320 Cues**
Program up to 16 receivers with 1 transmitter and have access to all 320 cues in Step Fire, Continuous Fire and All Fire modes from 1 transmitter.
 - **Unlimited Cues**
Program as many receivers as needed with the transmitter and fire many cues in parallel. Mix parallel and serial cues. For example have 2 receivers firing in parallel and have a 3rd and 4th receiver independently controlled.
- **Optional Waterproof Transmitter**
Purchase the optional waterproof transmitter for increased safety and control.
- **Transmitter Storage**
Compartment in the rear of the receiver to store the transmitter and arming keys.